Thuraya IP Upgrade

The latest Thuraya IP software version is Release 1.1.0.2

Release date: June 2014

RELEASE NOTES:

New in release 1.1.0.2

- M2M Watchdog
- Remote Access
- Configuration Transfer
- Streaming Counter and Alert
- Supporting "Cisco Jabber video" conferencing
- Changing URL for "Upgrade Modem Software" button under Properties screen
- The error code (41 and 42) reporting and handling on the webMMI is enhanced
- wMMI updated with correct company name & logo

UPGRADING THE THURAYA IP

In order to upgrade software you must first connect to the Internet and follow the steps listed below:

1. Connect your PC/Notebook to the Internet using Thuraya IP (satellite service), wired LAN, or dial up connection.

2. Go to www.thuraya.com or use the Upgrade link on the Properties Page if connected to the Thuraya IP.

3. Go to the web site area for Thuraya IP updates.

4. To download, select the latest upgrade package. The browser proceeds to retrieve the package.

5. Once the package is downloaded, you are prompted to execute the package. Select **Yes** and the upgrader application will self-extract onto the PC's hard drive.

6. Once the package is installed, it puts a shortcut on the desktop and prompts you to **upgrade now**. Make sure the Thuraya IP is now connected to the PC via

Ethernet (recommended) or USB and is powered up. Select the upgrade option on the PC, and the program will allow you to upgrade the terminal.

7. The upgrader will query the current software version of the terminal. You should choose whether you want to upgrade to the newer version of software.

8. If you choose to upgrade the terminal, the process automatically downloads the new release of software and forces a terminal reboot.

9. When the terminal returns from reboot, you can verify that the download was successful via the ***Properties*** page in the wMMI.

10. Once loaded onto a PC, the upgrade program can be used to upgrade any number of Thuraya IP terminals. Just connect them one at a time and execute the upgrade program.